

Quiz Week 7
ECE 656: Electronic Conduction In Semiconductors
Mark Lundstrom
Purdue University, Fall 2017

- 1) Why is the BTE harder to solve in the presence of a B-field?
 - a) Because we are no longer near equilibrium.
 - b) Because non-degenerate statistics must be used.
 - c) Because the cross product makes the math more difficult.
 - d) Because the gradient in momentum space can no longer be approximated by the gradient of f_S .
 - e) Because the gradient in position space can no longer be approximated by the gradient of f_S .

- 2) In this equation, $\vec{J}_n = \sigma_S \vec{E} - \sigma_S \mu_H (\vec{E} \times \vec{B})$, what is μ_H ?
 - a) The mobility.
 - b) The effective mobility.
 - c) The conductivity mobility.
 - d) The chemical potential.
 - e) The Hall mobility.

- 3) What is the quantity, $\frac{\langle\langle \tau_m^2 \rangle\rangle}{\langle\langle \tau_m \rangle\rangle^2}$, called?
 - a) The Hall mobility.
 - b) The Hall coefficient.
 - c) The Hall factor.
 - d) The Hall concentration.
 - e) The Hall parameter.

- 4) What quantity does a Hall effect measurement find?
 - a) The Hall mobility.
 - b) The mobility.
 - c) The Hall concentration.
 - d) The carrier concentration.
 - e) The Hall resistivity.

(continued on next page)

- 5) What does the criterion $\omega_c \tau_m \ll 1$ imply?
- Electrons scattering many times before completing a cyclotron orbit.
 - The magnetic field is low.
 - Shubnikov-deHaas oscillations will not be observed.
 - All of the above.
 - None of the above.
- 6) Assume that $\vec{B} = B_z \hat{z}$ what is J_y according to $J_i = \sigma_S \mathcal{E}_i - \sigma_S \mu_H \epsilon_{ijk} \mathcal{E}_j B_k$?
- $J_y = \sigma_S \mathcal{E}_y$
 - $J_y = -\sigma_S \mu_H \mathcal{E}_x B_z$
 - $J_y = +\sigma_S \mu_H \mathcal{E}_x B_z$
 - $J_y = \sigma_S \mathcal{E}_y - \sigma_S \mu_H \mathcal{E}_x B_z$
 - $J_y = \sigma_S \mathcal{E}_y + \sigma_S \mu_H \mathcal{E}_x B_z$
- 7) We have seen that for parabolic bands in 2D with non-degenerate conditions, $\langle\langle \tau_m \rangle\rangle = \tau_0 \Gamma(s+2)/\Gamma(2)$. What is the Hall coefficient, $r_H \equiv \langle\langle \tau_m^2 \rangle\rangle / \langle\langle \tau_m \rangle\rangle^2$ is 2D?
- $r_H = \Gamma(2s+2)/[\Gamma(2)]$.
 - $r_H = \Gamma(2s+2)\Gamma(2)/[\Gamma(s+2)]^2$
 - $r_H = \Gamma(2s+2)\Gamma(s+2)/[\Gamma(2)]^2$
 - $r_H = \Gamma(s+2)\Gamma(2)/[\Gamma(2s+2)]^2$
 - $r_H = \Gamma(3s+2)\Gamma(2)/[\Gamma(2s+2)]^2$.